



# AUDIO - VISUAL STATION

**MODEL : PA-1600 / PA-2600 / PA-3500**

## PRODUCT FEATURES

- Total 5 microphone inputs (Input 1 & 2 can be changed to Line IN by Switch)
- MIC 1 has priority function (Can eliminate the function by a switch at the rear panel)
- Two Line outputs available (RCA 0db 0.755V)
- Isolated transformer for PC input in the front panel can avoid the HUM noise
- Available 4Ω/70/100V Speaker Output
- Six Zones individual output with 6 steps level control (60W/CH)
- Individual ON/OFF switch for each zone output with LED indicator
- Remote ON/OFF for main power
- 7 bands graphic EQ



Model	PA-1600	PA-2600	PA-3500
Watt (W)	4Ω / 180W	4Ω / 280W	4Ω / 380W
Power Consumption	230W	350W	450W
Power	AC 220V 50Hz		
Frequency Response	80Hz - 16KHz ± 3dB		
Graphic EQ	125 / 250 / 500 / 1K / 2K / 4K / 8K		
AUX Input	350mV / 100 Ohms		
MIC Input	5mV / 600 Ohms		
S/N Ratio	≥ 78dB		
T.H.D.	≤ 0.1% (AT 1KHz)		
Output Mode	COM 4-16 Ohms - 70V - 100V Individual 6 Zone Output with 6 Steps Volume Control (Each Zone Max. Power is 60W)		
Size	432mm (W) x 330mm (D) x 88mm (H)		
Weight	11KG	12KG	14KG

\* Weight and dimensions indicated above are approximately. Specifications are subject to change without notice.



# AUDIO - VISUAL STATION

型 號 : PA-1600 / PA-2600 / PA-3500

## 產品特色

- 合共5路話筒輸入(其中兩路輸入可以通過機背開關轉換成線路輸入)
- MIC 1提供優先強播功能(可使用機背的開關停止此功能)
- 兩路線路輸出(RCA 0db 0.755V)
- 前面板的PC輸入口連結一個全頻式隔離變壓器，可以有效地解決由於地電平不同所產生的交流聲
- 同時擁有4Ω/70/100V揚聲器輸出
- 6個獨立分區輸出控制器，6種不同等級的控制令輸出音量的衰減更加細緻
- 每個獨立分區可以通過開關直接控制，並且有指示燈顯示當時的狀態
- 遙控接口負責控制本機電源的狀態
- 7段圖像式均衡器



型 號	PA-1600	PA-2600	PA-3500
功 率 (W)	4Ω / 180W	4Ω / 280W	4Ω / 380W
最大功耗	230W	350W	450W
供電電源	AC 220V 50Hz		
頻率響應	80Hz - 16KHz ± 3dB		
圖像均衡器	125 / 250 / 500 / 1K / 2K / 4K / 8K		
輔助輸入	350mV / 100 Ohms		
咪高風輸入	5mV / 600 Ohms		
訊噪比	≥ 78dB		
失真率	≤ 0.1% (AT 1KHz)		
輸出方式	COM 4-16 Ohms - 70V - 100V 6 分區獨立輸出，每區最大 60 瓦， 分六檔調節		
尺 寸	432mm (W) x 330mm (D) x 88mm (H)		
重 量	11公斤	12公斤	14公斤

\* 重量和尺寸均為約數，產品說明有所變更時，本公司恕不另行通知。