



Sunny 512BU / Sunny 512B 电脑灯控制台

- 512 个 DMX 通道，2 个光隔离 DMX 输出端口。
- 控制 32 台 16 通道电脑灯。
- LCD 显示。
- 16 个通道推杆，1 个速度控制推杆，2 个数据轮控制 16Bit 的 Tilt/Pan。
- 48 个走灯程序，共 1600 步。每步的速度、渐变参数独立设置。
- 48 场景储存。
- 15 个环境程序，快速调用不同的场景、走灯、手动运行（提灯）组合状态。
- 可同时运行 8 个走灯程序、48 个场景，并可同时对 32 台电脑灯进行提灯操作。
- USB 盘数据文件备份（只有 Sunny512BU）。
- 走灯程序音乐触发。
- 关机数据保存。
- 可选配 12V 鹅颈工作灯。
- 电源：AC 100V-240V，50-60Hz
- 尺寸：482mm × 400mm × 105mm
- 净重：约 8Kg
- 512 DMX channels with 2 optical isolated outputs.
- 32 units with 16 DMX channels each.
- LCD display.
- 16 channel faders, 1 chase speed fader, 2 modulation Wheel for 16 bit of Tilt/Pan.
- 48 chases, total 1600 steps. Speed and Cross time of each step can be set respectively.
- 48 scenes.
- 15 environment programs to output the combination, which are composed of different scenes, chases and manual output quickly.
- 8 chases, 48 scenes can be run simultaneously. At most 32 unit can be Manual operated.
- Backup or restore with USB Flash drive (Sunny 512BU only).
- Music trigger function for Chase.
- The Data auto-saves.
- Option: 12V Gooseneck lamp with BNC Socket
- Power supply: AC 100-240V, 50-60Hz.
- Size: 483mm × 400mm × 105mm
- Net weight: 8Kg approx