

AUDIO-VISUAL STATION



Professional Four Zone Matrix Mixer

MM-64



Product Overview

MM-64 is a 4 Zone Matrix Mixer with MP3 Player. It provides a versatile and user friendly system delivery up to five external audio inputs. Two Microphone inputs have Phantom Power and Gain control in the back side panel. The priority function for paging is saved in the Input 1.

Four inputs and MP3 Player can be selected to any Zone or Multi-Zone by each DIP switch. Simple wired remote control for each output zone when you plug in the 6.3mm stereo jack. The maximum level is controlled by the each channel knob on the front panel. A LED will light on if the zone has any signal coming. You can easy to monitor any zone output by the headphone plug-in.

Key Features :

- * Any combination of inputs to any output
- * Individual volume control for each Zone
- * Wired Remote Control for each output zone
- * 3 XLR balanced microphone inputs
- * Phantom power ready for microphone input
- * Stereo RCA input
- * Priority control for Input 1
- * 3.5mm stereo socket for mobile phone or external audio source
- * Built-in MP3 Player & High Sensitivity FM Radio
- * Provide output monitor function
- * 1 U Rackmount size for easy installation

Specifications :

- * Consumption Power : 10W
- * Power Supply : 220V 50/60 Hz
- * Frequency Response : 20 Hz ~ 20KHz (± 3 dB)
- * Input Sensitivity : Input 1 ~ Input 3 : (Mic -50 dB Line : - 15 dB)
: Input 4 : -20 dB
: Input 5 : -15 dB
- * Harmonic Distortion : < 0.2 %
- * Signal / Noise Ration : Mic ≥ 65 dB Aux / Line ≥ 80 dB
- * Controls : Input Volume Control
: Monitor Volume Control
: Zone Volume Control
: Input Assign Switch
: Monitor Assign Switch
- * Output Impedance : 600 Ω Balanced
- * BGM : MP3 Player
- * Input 1 Priority : Yes
- * Rec Out : 1 V
- * MP3 Player : Yes
- * Dimension : 480 * 200 * 44mm
- * Output : Main output : 11V
: Monitor Output : 1V



* Specifications and design are subject to change without notice